

B3010 RF Single Colour Receiver & Controller

This RF (Radio Frequency) Single Colour Remote Control and Dimmer/Receiver can be used with single colour MicroLED strips. With the remote control, you can easily adjust the brightness of the LED strip



PHYSICAL DATA

- Handset measures 86mm x 40mm x 7mm (LxWxH)
- Driver measures 64mm x 20mm x 8.5mm
- 115mm long connection wires
- IP63

ELECTRICAL DATA

- 5v – 24v DC input
- Max load 10A
- Max output power 120w (12v) or 240w (24v)
- 256 levels of brightness or use one of 6 pre-set levels of 10%, 20%, 40%, 60%, 80%, 100% with 1kHz PWM frequency.
- CR2025 battery for handset (supplied)
- Transmission frequency 433.92Mhz

INSTALLATION

The hand-held controller requires pairing to the driver. One remote can control multiple drivers, or multiple remotes can control one driver. Driver requires a suitable power supply 12v – 24v .

COMPLIANCE & WARRANTY

- 2 year warranty
- CE / RoHS Compliant